

## CLAIMS

Sub A1  
5 1. A method for operating a transistor cell comprising an input terminal for receiving an input signal, an output terminal for transmitting an output signal, a grounded base transistor coupled between the input and output terminals, and a current mirror coupled between the input and output terminals, the method comprising biasing the transistor cell to establish a bias current in the grounded base transistor and the current mirror when the input signal is zero.

10 2. A method according to claim 1 further including limiting the input signal to a range in which the output function of the transistor cell approximates a square-law.

Sub A2  
15 3. A method according to claim 2 further including adjusting the bias current, thereby adjusting the input impedance of the cell.

4. A method according to claim 1 wherein biasing the transistor cell includes: coupling a bias signal to the base of the grounded base transistor; and varying the bias signal with temperature such that it causes the bias current through the grounded base transistor and the current mirror to be proportional to absolute  
20 temperature.

5. A method according to claim 1 wherein:  
the current mirror is coupled to a power supply terminal; and  
biasing the transistor cell includes maintaining the base of the grounded base  
25 transistor at about  $2V_{BE}$  from the voltage of the power supply terminal.

6. A method according to claim 1 further including isolating the current mirror from the output terminal.

30 7. A method according to claim 6 wherein isolating the current mirror includes coupling a cascode transistor between the output terminal and the current mirror.

Sub A3  
8. A squaring cell comprising:  
an input terminal;

Sub  
#3  
included  
5 an output terminal;  
a grounded base transistor coupled between the input and output terminals;  
a current mirror coupled between the input and output terminals; and  
a bias signal generator coupled to the grounded base transistor to establish a bias  
current through the grounded base transistor and the current mirror.

9. A squaring cell according to claim 8 further including a cascode transistor  
coupled between the current mirror and the output terminal.

10 10. A squaring cell according to claim 8 wherein the current mirror is coupled to a  
power supply terminal, and the bias signal generator maintains the base of the grounded base  
transistor at about  $2V_{BE}$  from the voltage of the power supply terminal.

11. A squaring cell according to claim 8 wherein the current mirror includes:  
15 a diode-connected transistor coupled between the input terminal and a power supply  
terminal; and  
a mirror transistor having a collector coupled to the output terminal, a base coupled to  
the input terminal, and an emitter coupled to the power supply terminal.

20 12. A squaring cell according to claim 8 wherein:  
the grounded base transistor has a collector coupled to the output terminal, a base for  
receiving the bias signal, and an emitter coupled to the input terminal;  
the current mirror includes:

25 a diode-connected transistor having a collector and base coupled to the input  
terminal and an emitter coupled to a power supply terminal, and  
a mirror transistor having a collector coupled to the output terminal, a base  
coupled to the input terminal, and an emitter coupled to the power supply terminal.

30 13. A squaring cell according to claim 8 wherein the bias signal generator  
generates a bias signal that varies with temperature such that it causes the bias current  
through each of the transistors to be proportional to absolute temperature.

14. A squaring cell according to claim 8 wherein the bias signal generator  
includes:

a current source coupled to the diode connected transistors to cause a bias current to flow through the diode connected transistors.

5

Add A4

[illegible]